

## Actuator LA33 With endstop reached

# **Connection diagram**





### **Connection diagram**

			Power	AMP	Deutsch
		BROWN	2	2	2- F-F) -1
		BLUE	1		
			Signal	AN	ЛP
	Supply for feedback	+ RED	2		
				Deut	tsch
	Digital output	YELLOW	5	6	
1 4				DC .	50
<b>L</b> '.	Digital output	GREEN	6		
	Supply for feedback	- BLACK	1		



If you wish to use the endstop reached, you will have to keep power on the Brown, Blue, Red and Black wires, otherwise the signal will be lost.

#### I/O specifications

Input/Output	Specification	Comments		
Description	The actuator can be equipped with electronically controlled Endstop reached out.			
Brown	12 - 24 V DC (+/-) 12 V ± 20 % 24 V ± 10 %	To extend actuator: Connect Brown to positive To retract actuator: Connect Brown to negative		
Blue	Under normal conditions: 12 V, max. 13 A 24 V, max. 9 A	To extend actuator: Connect Blue to negative To retract actuator: Connect Blue to positive		
Red	Signal power supply (+) 12-24 V DC	Current consumption:		
Black	Signal power supply GND (-)	Max. 40 mA during run and pause There will be accrued a higher inrush current		
Green	Endstop reached out	Output voltage min. VIN - 2 V		
Yellow	Endstop reached in	Source current max. 100 mA  NOT potential free		
Violet	Not to be connected			
White	Not to be connected			

#### Terms of use

Terms of use
LINAK® takes great care in providing accurate and up-to-date information on its products. However, the
user is responsible for determining the suitability of LINAK products for a specific application.
Due to continual development, LINAK products are subject to frequent modifications and changes.
LINAK reserves the rights to conduct modifications, updates, and changes without any prior notice. For
the same reason, LINAK cannot guarantee the correctness and actual status of imprinted information on
its products.

LINAK uses its best efforts to fulfil orders. However, for the reasons mentioned above, LINAK cannot guarantee availability of any particular product at any given time. LINAK reserves the right to discontinue the sale of any product displayed on its website or listed in its catalogues or in other written material created and produced by LINAK, LINAK subsidiaries, or LINAK affiliates.

All sales are subject to the "Standard Terms of Sale and Delivery for LINAK A/S" available on LINAK websites. LINAK and the LINAK logotype are registered trademarks of LINAK A/S. All rights reserved.

